

Project:	Type:
Item. No.	
Location:	
Notes:	

classic flanged

recessed downlights

standard features

electrical

- Input operating voltage: 120V, 60Hz
- Power cord: 18/2 SPT-2 (black)
- Four wiring configurations listed in ordering information below

lighting source

- Lamps: 35HR16, 40R14, 8WPAR20 LED (EQUIV 50W)
- Canisters use reflector-type lamps

dimensions

- Height: 2⁷/₈" , 3⁵/₈"
- Diameter: 3 1/4"

construction

- Steel

finish

- Painted: black (BK)
 - Plated: antique brass (AB), brushed nickel (BN), polished brass (PB), polished chrome (PC)
- (Not all finishes available for select products; see ordering information below)

installation

- Adjustable mounting ring, spring clips or screw holes
- Adjustable ring (R) installation hole diameter 3 3/8"
- Spring clips (SC) installation hole diameter 3 3/4"

warranty/certification

- 1 year warranty
- UL and cUL

options

- Other finishes
- Other lamp options
- Contact factory for custom options



FA35
ring mount
antique brass



*shown FB50 (spring clip mount with polished chrome finish)

FB50
spring clip mount
polished chrome



FA40
screw hole mount
polished brass



FA40
ring mount
black

Fixtures require either a power cordset or an appropriate control device. See Controls, Lamps & Accessories on our website.



see following pages for classic flanged ordering information

ordering information FA series (ring mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-1310	FA35-1-AB-R	2 7/8"	10' power cord with rollswitch	AB	35HR16
N/A	2020-1311	FA35-1-BK-R	2 7/8"	10' power cord with rollswitch	BK	35HR16
N/A	2020-1312	FA35-1-PB-R	2 7/8"	10' power cord with rollswitch	PB	35HR16
N/A	2020-1313	FA35-1-PC-R	2 7/8"	10' power cord with rollswitch	PC	35HR16
N/A	2020-1314	FA35-1-BN-R	2 7/8"	10' power cord with rollswitch	BN	35HR16
2000-0221	2020-1320	FA35-2-AB-R	2 7/8"	10' power cord with rollswitch, 30" female	AB	35HR16
2000-0222	2020-1321	FA35-2-BK-R	2 7/8"	10' power cord with rollswitch, 30" female	BK	35HR16
2000-0224	2020-1322	FA35-2-PB-R	2 7/8"	10' power cord with rollswitch, 30" female	PB	35HR16
2000-0225	2020-1323	FA35-2-PC-R	2 7/8"	10' power cord with rollswitch, 30" female	PC	35HR16
2000-0223	2020-1324	FA35-2-BN-R	2 7/8"	10' power cord with rolls witch, 30" female	BN	35HR16
2000-0201	2020-1330	FA35-3-AB-R	2 7/8"	30" male & female	AB	35HR16
2000-0202	2020-1331	FA35-3-BK-R	2 7/8"	30" male & female	BK	35HR16
2000-0203	2020-1332	FA35-3-PB-R	2 7/8"	30" male & female	PB	35HR16
2000-0204	2020-1333	FA35-3-PC-R	2 7/8"	30" male & female	PC	35HR16
2000-0217	2020-1334	FA35-3-BN-R	2 7/8"	30" male & female	BN	35HR16
2000-0209	2020-1340	FA35-4-AB-R	2 7/8"	30" male	AB	35HR16
2000-0210	2020-1341	FA35-4-BK-R	2 7/8"	30" male	BK	35HR16
2000-0211	2020-1342	FA35-4-PB-R	2 7/8"	30" male	PB	35HR16
2000-0212	2020-1343	FA35-4-PC-R	2 7/8"	30" male	PC	35HR16
2000-0219	2020-1344	FA35-4-BN-R	2 7/8"	30" male	BN	35HR16
N/A	2020-2310	FA40-1-AB-R	2 7/8"	10' power cord with rollswitch	AB	40R14
N/A	2020-2311	FA40-1-BK-R	2 7/8"	10' power cord with rollswitch	BK	40R14
N/A	2020-2312	FA40-1-PB-R	2 7/8"	10' power cord with rollswitch	PB	40R14
N/A	2020-2313	FA40-1-PC-R	2 7/8"	10' power cord with rollswitch	PC	40R14
N/A	2020-2314	FA40-1-BN-R	2 7/8"	10' power cord with rollswitch	BN	40R14
2000-0289	2020-2320	FA40-2-AB-R	2 7/8"	10' power cord with rollswitch, 30" female	AB	40R14
2000-0290	2020-2321	FA40-2-BK-R	2 7/8"	10' power cord with rollswitch, 30" female	BK	40R14
2000-0291	2020-2322	FA40-2-PB-R	2 7/8"	10' power cord with rollswitch, 30" female	PB	40R14
2000-0292	2020-2323	FA40-2-PC-R	2 7/8"	10' power cord with rollswitch, 30" female	PC	40R14
2000-0272	2020-2324	FA40-2-BN-R	2 7/8"	10' power cord with rollswitch, 30" female	BN	40R14
2000-0251	2020-2330	FA40-3-AB-R	2 7/8"	30" male & female	AB	40R14
2000-0252	2020-2331	FA40-3-BK-R	2 7/8"	30" male & female	BK	40R14
2000-0253	2020-2332	FA40-3-PB-R	2 7/8"	30" male & female	PB	40R14
2000-0254	2020-2333	FA40-3-PC-R	2 7/8"	30" male & female	PC	40R14
2000-0267	2020-2334	FA40-3-BN-R	2 7/8"	30" male & female	BN	40R14
2000-0255	2020-2340	FA40-4-AB-R	2 7/8"	30" male	AB	40R14
2000-0256	2020-2341	FA40-4-BK-R	2 7/8"	30" male	BK	40R14
2000-0257	2020-2342	FA40-4-PB-R	2 7/8"	30" male	PB	40R14
2000-0258	2020-2343	FA40-4-PC-R	2 7/8"	30" male	PC	40R14
2000-0268	2020-2344	FA40-4-BN-R	2 7/8"	30" male	BN	40R14

ordering information FA series (spring clip mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-1410	FA35-1-AB-SC	2 7/8"	10' power cord with rollswitch	AB	35HR16
N/A	2020-1411	FA35-1-BK-SC	2 7/8"	10' power cord with rollswitch	BK	35HR16
N/A	2020-1412	FA35-1-PB-SC	2 7/8"	10' power cord with rollswitch	PB	35HR16
N/A	2020-1413	FA35-1-PC-SC	2 7/8"	10' power cord with rollswitch	PC	35HR16
N/A	2020-1414	FA35-1-BN-SC	2 7/8"	10' power cord with rollswitch	BN	35HR16
2000-0226	2020-1420	FA35-2-AB-SC	2 7/8"	10' power cord with rollswitch, 30" female	AB	35HR16
2000-0227	2020-1421	FA35-2-BK-SC	2 7/8"	10' power cord with rollswitch, 30" female	BK	35HR16
2000-0229	2020-1422	FA35-2-PB-SC	2 7/8"	10' power cord with rollswitch, 30" female	PB	35HR16
2000-0230	2020-1423	FA35-2-PC-SC	2 7/8"	10' power cord with rollswitch, 30" female	PC	35HR16
2000-0228	2020-1424	FA35-2-BN-SC	2 7/8"	10' power cord with rollswitch, 30" female	BN	35HR16
2000-0205	2020-1430	FA35-3-AB-SC	2 7/8"	30" male & female	AB	35HR16
2000-0206	2020-1431	FA35-3-BK-SC	2 7/8"	30" male & female	BK	35HR16
2000-0207	2020-1432	FA35-3-PB-SC	2 7/8"	30" male & female	PB	35HR16
2000-0208	2020-1433	FA35-3-PC-SC	2 7/8"	30" male & female	PC	35HR16
2000-0218	2020-1434	FA35-3-BN-SC	2 7/8"	30" male & female	BN	35HR16
2000-0213	2020-1440	FA35-4-AB-SC	2 7/8"	30" male	AB	35HR16
2000-0214	2020-1441	FA35-4-BK-SC	2 7/8"	30" male	BK	35HR16
2000-0215	2020-1442	FA35-4-PB-SC	2 7/8"	30" male	PB	35HR16
2000-0216	2020-1443	FA35-4-PC-SC	2 7/8"	30" male	PC	35HR16
2000-0220	2020-1444	FA35-4-BN-SC	2 7/8"	30" male	BN	35HR16
N/A	2020-2410	FA40-1-AB-SC	2 7/8"	10' power cord with rollswitch	AB	40R14
N/A	2020-2411	FA40-1-BK-SC	2 7/8"	10' power cord with rollswitch	BK	40R14
N/A	2020-2412	FA40-1-PB-SC	2 7/8"	10' power cord with rollswitch	PB	40R14
N/A	2020-2413	FA40-1-PC-SC	2 7/8"	10' power cord with rollswitch	PC	40R14
N/A	2020-2414	FA40-1-BN-SC	2 7/8"	10' power cord with rollswitch	BN	40R14
2000-0293	2020-2420	FA40-2-AB-SC	2 7/8"	10' power cord with rollswitch, 30" female	AB	40R14
2000-0294	2020-2421	FA40-2-BK-SC	2 7/8"	10' power cord with rollswitch, 30" female	BK	40R14
2000-0295	2020-2422	FA40-2-PB-SC	2 7/8"	10' power cord with rollswitch, 30" female	PB	40R14
2000-0296	2020-2423	FA40-2-PC-SC	2 7/8"	10' power cord with rollswitch, 30" female	PC	40R14
TBD	2020-2424	FA40-2-BN-SC	2 7/8"	10' power cord with rollswitch, 30" female	BN	40R14
2000-0259	2020-2430	FA40-3-AB-SC	2 7/8"	30" male & female	AB	40R14
2000-0260	2020-2431	FA40-3-BK-SC	2 7/8"	30" male & female	BK	40R14
2000-0261	2020-2432	FA40-3-PB-SC	2 7/8"	30" male & female	PB	40R14
2000-0262	2020-2433	FA40-3-PC-SC	2 7/8"	30" male & female	PC	40R14
2000-0269	2020-2434	FA40-3-BN-SC	2 7/8"	30" male & female	BN	40R14
2000-0263	2020-2440	FA40-4-AB-SC	2 7/8"	30" male	AB	40R14
2000-0264	2020-2441	FA40-4-BK-SC	2 7/8"	30" male	BK	40R14
2000-0265	2020-2442	FA40-4-PB-SC	2 7/8"	30" male	PB	40R14
2000-0266	2020-2443	FA40-4-PC-SC	2 7/8"	30" male	PC	40R14
2000-0270	2020-2444	FA40-4-BN-SC	2 7/8"	30" male	BN	40R14

ordering information FA series (screw hole mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-1210	FA35-1-AB-SH	2 7/8"	10' power cord with rollswitch	AB	35HR16
N/A	2020-1211	FA35-1-BK-SH	2 7/8"	10' power cord with rollswitch	BK	35HR16
N/A	2020-1212	FA35-1-PB-SH	2 7/8"	10' power cord with rollswitch	PB	35HR16
N/A	2020-1213	FA35-1-PC-SH	2 7/8"	10' power cord with rollswitch	PC	35HR16
2000-0239	2020-1220	FA35-2-AB-SH	2 7/8"	10' power cord with rollswitch, 30" female	AB	35HR16
2000-0240	2020-1221	FA35-2-BK-SH	2 7/8"	10' power cord with rollswitch, 30" female	BK	35HR16
2000-0241	2020-1222	FA35-2-PB-SH	2 7/8"	10' power cord with rollswitch, 30" female	PB	35HR16
2000-0242	2020-1223	FA35-2-PC-SH	2 7/8"	10' power cord with rollswitch, 30" female	PC	35HR16
2000-0231	2020-1230	FA35-3-AB-SH	2 7/8"	30" male & female	AB	35HR16
2000-0232	2020-1231	FA35-3-BK-SH	2 7/8"	30" male & female	BK	35HR16
2000-0233	2020-1232	FA35-3-PB-SH	2 7/8"	30" male & female	PB	35HR16
2000-0234	2020-1233	FA35-3-PC-SH	2 7/8"	30" male & female	PC	35HR16
2000-0235	2020-1240	FA35-4-AB-SH	2 7/8"	30" male	AB	35HR16
2000-0236	2020-1241	FA35-4-BK-SH	2 7/8"	30" male	BK	35HR16
2000-0237	2020-1242	FA35-4-PB-SH	2 7/8"	30" male	PB	35HR16
2000-0238	2020-1243	FA35-4-PC-SH	2 7/8"	30" male	PC	35HR16
N/A	2020-2210	FA40-1-AB-SH	2 7/8"	10' power cord with rollswitch	AB	40R14
N/A	2020-2211	FA40-1-BK-SH	2 7/8"	10' power cord with rollswitch	BK	40R14
N/A	2020-2212	FA40-1-PB-SH	2 7/8"	10' power cord with rollswitch	PB	40R14
N/A	2020-2230	FA40-1-PC-SH	2 7/8"	10' power cord with rollswitch	PC	40R14
2000-0297	2020-2220	FA40-2-AB-SH	2 7/8"	10' power cord with rollswitch, 30" female	AB	40R14
2000-0297	2020-2221	FA40-2-BK-SH	2 7/8"	10' power cord with rollswitch, 30" female	BK	40R14
2000-0297	2020-2222	FA40-2-PB-SH	2 7/8"	10' power cord with rollswitch, 30" female	PB	40R14
2000-0297	2020-2223	FA40-2-PC-SH	2 7/8"	10' power cord with rollswitch, 30" female	PC	40R14
2000-0281	2020-2230	FA40-3-AB-SH	2 7/8"	30" male & female	AB	40R14
2000-0282	2020-2231	FA40-3-BK-SH	2 7/8"	30" male & female	BK	40R14
2000-0283	2020-2232	FA40-3-PB-SH	2 7/8"	30" male & female	PB	40R14
2000-0284	2020-2233	FA40-3-PC-SH	2 7/8"	30" male & female	PC	40R14
2000-0285	2020-2240	FA40-4-AB-SH	2 7/8"	30" male	AB	40R14
2000-0286	2020-2241	FA40-4-BK-SH	2 7/8"	30" male	BK	40R14
2000-0287	2020-2242	FA40-4-PB-SH	2 7/8"	30" male	PB	40R14
2000-0288	2020-2243	FA40-4-PC-SH	2 7/8"	30" male	PC	40R14

ordering information FB series (ring mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-3210	FB50-1-AB-R	3 5/8"	10' power cord with rollswitch	AB	8WPAR20 LED (50W Equiv)
N/A	2020-3211	FB50-1-BK-R	3 5/8"	10' power cord with rollswitch	BK	8WPAR20 LED (50W Equiv)
N/A	2020-3213	FB50-1-PC-R	3 5/8"	10' power cord with rollswitch	PC	8WPAR20 LED (50W Equiv)
N/A	2020-3214	FB50-1-BN-R	3 5/8"	10' power cord with rollswitch	BN	8WPAR20 LED (50W Equiv)
2000-0320	2020-3220	FB50-2-AB-R	3 5/8"	10' power cord with rollswitch, 30" female	AB	8WPAR20 LED (50W Equiv)
2000-0321	2020-3221	FB50-2-BK-R	3 5/8"	10' power cord with rollswitch, 30" female	BK	8WPAR20 LED (50W Equiv)
2000-0323	2020-3223	FB50-2-PC-R	3 5/8"	10' power cord with rollswitch, 30" female	PC	8WPAR20 LED (50W Equiv)
2000-0324	2020-3224	FB50-2-BN-R	3 5/8"	10' power cord with rollswitch, 30" female	BN	8WPAR20 LED (50W Equiv)
2000-0301	2020-3230	FB50-3-AB-R	3 5/8"	30" male & female	AB	8WPAR20 LED (50W Equiv)
2000-0302	2020-3231	FB50-3-BK-R	3 5/8"	30" male & female	BK	8WPAR20 LED (50W Equiv)
2000-0304	2020-3233	FB50-3-PC-R	3 5/8"	30" male & female	PC	8WPAR20 LED (50W Equiv)
2000-0305	2020-3234	FB50-3-BN-R	3 5/8"	30" male & female	BN	8WPAR20 LED (50W Equiv)
2000-0306	2020-3240	FB50-4-AB-R	3 5/8"	30" male	AB	8WPAR20 LED (50W Equiv)
2000-0307	2020-3241	FB50-4-BK-R	3 5/8"	30" male	BK	8WPAR20 LED (50W Equiv)
2000-0309	2020-3243	FB50-4-PC-R	3 5/8"	30" male	PC	8WPAR20 LED (50W Equiv)
2000-0310	2020-3244	FB50-4-BN-R	3 5/8"	30" male	BN	8WPAR20 LED (50W Equiv)

ordering information FB series (spring clip mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-3310	FB50-1-AB-SC	3 5/8"	10' power cord with rollswitch	AB	8WPAR20 LED (50W Equiv)
N/A	2020-3311	FB50-1-BK-SC	3 5/8"	10' power cord with rollswitch	BK	8WPAR20 LED (50W Equiv)
N/A	2020-3313	FB50-1-PC-SC	3 5/8"	10' power cord with rollswitch	PC	8WPAR20 LED (50W Equiv)
N/A	2020-3314	FB50-1-BN-SC	3 5/8"	10' power cord with rollswitch	BN	8WPAR20 LED (50W Equiv)
2000-0325	2020-3320	FB50-2-AB-SC	3 5/8"	10' power cord with rollswitch, 30" female	AB	8WPAR20 LED (50W Equiv)
2000-0326	2020-3321	FB50-2-BK-SC	3 5/8"	10' power cord with rollswitch, 30" female	BK	8WPAR20 LED (50W Equiv)
2000-0328	2020-3323	FB50-2-PC-SC	3 5/8"	10' power cord with rollswitch, 30" female	PC	8WPAR20 LED (50W Equiv)
2000-0329	2020-3324	FB50-2-BN-SC	3 5/8"	10' power cord with rollswitch, 30" female	BN	8WPAR20 LED (50W Equiv)
2000-0311	2020-3335	FB50-3-AB-SC	3 5/8"	30" male & female	AB	8WPAR20 LED (50W Equiv)
2000-0312	2020-3336	FB50-3-BK-SC	3 5/8"	30" male & female	BK	8WPAR20 LED (50W Equiv)
2000-0314	2020-3333	FB50-3-PC-SC	3 5/8"	30" male & female	PC	8WPAR20 LED (50W Equiv)
2000-0329	2020-3334	FB50-3-BN-SC	3 5/8"	30" male & female	BN	8WPAR20 LED (50W Equiv)
2000-0315	2020-3340	FB50-4-AB-SC	3 5/8"	30" male	AB	8WPAR20 LED (50W Equiv)
2000-0316	2020-3341	FB50-4-BK-SC	3 5/8"	30" male	BK	8WPAR20 LED (50W Equiv)
2000-0318	2020-3343	FB50-4-PC-SC	3 5/8"	30" male	PC	8WPAR20 LED (50W Equiv)
2000-0319	2020-3344	FB50-4-BN-SC	3 5/8"	30" male	BN	8WPAR20 LED (50W Equiv)

ordering information FB series (screw hole mount)

item number t-shape female	item number standard female	catalog number	height	wiring	finish	lamp
N/A	2020-3110	FB50-1-AB-SH	3 5/8"	10' power cord with rollswitch	AB	8WPAR20 LED (50W Equiv)
N/A	2020-3111	FB50-1-BK-SH	3 5/8"	10' power cord with rollswitch	BK	8WPAR20 LED (50W Equiv)
N/A	2020-3112	FB50-1-PB-SH	3 5/8"	10' power cord with rollswitch	PB	8WPAR20 LED (50W Equiv)
2000-0340	2020-3120	FB50-2-AB-SH	3 5/8"	10' power cord with rollswitch, 30" female	AB	8WPAR20 LED (50W Equiv)
2000-0341	2020-3121	FB50-2-BK-SH	3 5/8"	10' power cord with rollswitch, 30" female	BK	8WPAR20 LED (50W Equiv)
2000-0342	2020-3122	FB50-2-PB-SH	3 5/8"	10' power cord with rollswitch, 30" female	PB	8WPAR20 LED (50W Equiv)
2000-0331	2020-3130	FB50-3-AB-SH	3 5/8"	30" male & female	AB	8WPAR20 LED (50W Equiv)
2000-0332	2020-3131	FB50-3-BK-SH	3 5/8"	30" male & female	BK	8WPAR20 LED (50W Equiv)
2000-0333	2020-3132	FB50-3-PB-SH	3 5/8"	30" male & female	PB	8WPAR20 LED (50W Equiv)
2000-0335	2020-3140	FB50-4-AB-SH	3 5/8"	30" male	AB	8WPAR20 LED (50W Equiv)
2000-0336	2020-3141	FB50-4-BK-SH	3 5/8"	30" male	BK	8WPAR20 LED (50W Equiv)
2000-0337	2020-3142	FB50-4-PB-SH	3 5/8"	30" male	PB	8WPAR20 LED (50W Equiv)

power cordset ordering information

item number t-shape female	item number standard female	catalog number	description
7000-0002	7000-0728	#211 cordset	10' cord with standard male plug, rollswitch, & rollswitch holder

lamps and parts

item number	description
350-1840	plastic mounting ring
337-250	socket & ring nut for medium base cans (FA, FB, FD)
398-1370	40R14 lamp (medium based)
398-995	35HR16 halogen lamp (medium based)
398-28	8WPAR20 LED (50W EQUIV)

See Controls, Lamps, and Accessories for additional options.