

IMPORTANT - READ BEFORE INSTALLATION:

- To reduce the risk of fire, electric shock, or injury to persons before attempting installation, unplug and verify there is no power going to the switch or to the cabinet the switch is installed in.
- Specialty Lighting recommends a qualified electrician preform the three level touch dimmer replacement installation or a person familiar with the construction and operation of electrical systems and the hazard involved. If not qualified, do not attempt installation. Contact a qualified electrician. Specialty Lighting offers no warranty for any repair not performed by Specialty Lighting.

Installing three level touch dimmer

1. Unplug and ensure no power is going to the switch or furniture.
2. Remove screws in corners of the box to remove dimmer box from furniture.
3. Remove 2 screws in the center of the ends of the box holding the box together where the dimmer components are held.
4. Cut the wires at the crimped-on connectors from the old dimmer to remove it from the box. Make note which wire the colored wire from the dimmer went with as you cut them for easier installation of the new dimmer.
5. Re-strip the insulation 1/2" from all wires on replacement dimmer.
6. Install the new dimmer.
 - a) Connect **gray wire** from replacement dimmer to the striped (ribbed) wires from the power cord and female connector(s) to the light with a suitable wire nut.
 - b) Connect **black wire** from replacement dimmer to the power cord solid (smooth) wire with a suitable wire nut.
 - c) Connect **brown wire** from replacement dimmer to the solid (smooth) wire from the female connector(s) to the light with a suitable wire nut.
 - d) Connect **yellow wire** from replacement dimmer to the touch lead wire with a suitable wire nut. This wire is normally a single stranded wire connected to something metal, such as a hinge, that is touched to activate the lights.
7. Reinstall the cover of the box making sure the wires are routed properly out the notches in the ends of the box. Secure with the 2 screws removed in Step 3.
8. Reattach dimmer box to the cabinet where it was removed.

